



A.P.N

PUNTO DE ACCESO A INTERNET

Si tu reloj llama y recibe llamadas pero no se conecta a internet, deberás enviar un SMS desde tu teléfono móvil particular al número del reloj con el siguiente mensaje de texto según el operador que hayas contratado para el Reloj. Una vez enviado espera a recibir el mensaje de respuesta para reiniciar el reloj

GUALARU

Gualaru Line:	pw,123456,apn,i.openmovil.tv,gualaru,opencable,21403#
Amena:	pw,123456,apn,orangeworld,orange,orange,21403#
Carrefour:	pw,123456,apn,carrefourinternet,,21403#
DigiMobil:	pw,123456,apn,internet.digimobil.es,digi,digi,21422#
Eurona:	pw,123456,apn,inet.es,,334030#
Euroski movil:	pw,123456,apn,gprs.eroskimovil.es,,21406#
Euskaltel Movil:	pw,123456,apn,i.euskaltel.mobi,,21403#
Happy móvil:	pw,123456,apn,internetph,,21403#
Hits mobile:	pw,123456,apn,tel.hitsmobile.es,,21406#
Jazztel:	pw,123456,apn,jazzinternet,,21421#
Lebara:	pw,123456,apn,gprsmov.lebaramobile.es,,21401#
Lycamobile:	pw,123456,apn,data.lycamobile.es,lmes,plus,21423#
Llamaya (contrato):	pw,123456,apn,internetmas,,21403#
Másmovil:	pw,123456,apn,internetmas,,21403#
MobilR:	pw,123456,apn,internet.mundo-r.com,,21403#
Movistar:	pw,123456,apn,telefonica.es,telefonica,telefonica,21407#
O2:	pw,123456,apn,telefonica.es,,21407#
Oceans:	pw,123456,apn,oceans.es,OCEANS,OCEANS,21407#
ONO:	pw,123456,apn,airtelwap.es,,21401#
Orange:	pw,123456,apn,orangeworld,orange,orange,21403#
Pepephone:	pw,123456,apn,internet,,21404#
PTV Telecom:	pw,123456,apn,datos,,21403#
SieteVOZ:	pw,123456,apn,inet.es,,21434#
Simyo:	pw,123456,apn,gprs-service.com,,1234,21419#
Telecable:	pw,123456,apn,internet.telecable.es,telecable,telecable,21406#
Tuenti móvil:	pw,123456,apn,tuenti.com,tuenti,tuenti,21405#
Vodafone:	pw,123456,apn,airtelwap.es,,21401#
Yoigo:	pw,123456,apn,internet,,21404#
FreedomPop:	pw,123456,apn,internetmas,,21403#
Republica movil:	pw,123456,apn,orangeworld,,21403#
Things Mobile:	pw,123456,apn,tm@,,23450#
Lowi:	pw,123456,apn,lowi.private.omv.es,,21406#